

SAFETY WARNINGS IMPORTANT SAFETY INFORMATION



Before you begin.

Read these instructions completely & carefully.



WARNING Risk of electrical shock. Disconnect power before servicing or installing luminaire.



WARNING Risk of injury or damage. Luminaire will fall if not installed properly. Follow installation instructions, NEC and local codes and best trade knowledge.



WARNING Risk of injury. Wear safety glasses and gloves during installation and servicing.




WARNING Risk of injury or damage. Mount only to a mechanically sound surface; All fixtures must be connected to a grounded, three-wire supply; All electrical connections must be capped with UL listed wire connectors rated 600V or higher; If supply wires are located within three inches of the LED driver, use wire rated for at least 90°C; Consult qualified electrician before installing.

Follow information on label & instructions regarding installation near combustible materials, insulation, and building materials & in Dry or Wet locations. Do not install in areas exposed to combustible vapors or gases. **This product must be installed by a person familiar with construction and operation of the product and the hazards involved, in accordance with the applicable installation. Be sure to ground product to avoid potential electrical shock or other potential hazard.** Use of accessory equipment not recommended by the manufacturer or installed inconsistent with instructions may cause an unsafe condition. Do not completely or partially block light emerging from product, as this could cause an unsafe condition. Do not allow other items to come into contact with the product, as this may cause an unsafe condition. **WARNING:** This product may contain chemicals known to the State of California to cause cancer, birth defects and/or other reproductive harm. Thoroughly wash your hands after installing, servicing, handling, cleaning, or otherwise touching this product. This device complies with FCC CFR Title 47 Part 15, Class A requirements for EMI/RFI.

INSTALLATION


Fig. 1



Step 1: Unpack & Inspect

Carefully remove fixture from packaging. Use gloves to prevent dirt and oils from transferring to the unit. Inspect the fixture for any defects before proceeding. Confirm the product ordered matches the product received.


Fig. 2



Step 2: Remove Access Plate

Remove retaining screw (a), then slide the entire plate in the direction shown in (b). Use the tab at (c) to lift the access plate and pull free of the chassis.


Fig. 3



Step 3: Make Connections

Reach into the hole (a) and pull the wired, luminaire disconnect out of the fixture, being careful to avoid wire abrasions. Use the poke-in connectors (b) on line-side of the luminaire disconnect to connect hot (black to black) and neutral (white to white). Connect ground to grounding screw (c) on the back side of the luminaire disconnect.


Fig. 4



Step 4: Relocate Access Plate

First slip the large tab of the access plate into the hole (a) and push forward so the two smaller tabs drop in as well. Again, be careful to avoid wire abrasions.


Fig. 5



Step 5: Secure Access Plate

Slide the entire plate in the direction shown at (a), then replace the retaining screw (b).

Fig. 6



Step 6: Suspended Mount

Suspended mounting can be achieved with the adjustable cable mounting kit (BLC48-ACC-CBLKIT15) as shown in (a1) & (a2) or with chain mounting kit (BLC48-ACC-PNDKIT06) as shown in (b). Both are sold separately. For each, ensure the hooks are securely installed in the fixture chassis.

APPLICATION ADVICE

- Do not touch LED diodes or connecting clips on the LED modules.
- This product is intended for application in indoor, dry and non-corrosive environments.

SAFETY WARNINGS | IMPORTANT SAFETY INFORMATION



Before you begin.

Read these instructions completely & carefully.



WARNING Risk of electrical shock. Disconnect power before servicing or installing luminaire.



WARNING Risk of injury or damage. Luminaire will fall if not installed properly. Follow installation instructions, NEC and local codes and best trade knowledge.



WARNING Risk of injury. Wear safety glasses and gloves during installation and servicing.



WARNING

Risk of injury or damage. Mount only to a mechanically sound surface; All fixtures must be connected to a grounded, three-wire supply; All electrical connections must be capped with UL listed wire connectors rated 600V or higher; If supply wires are located within three inches of the LED driver, use wire rated for at least 90°C; Consult qualified electrician before installing.

Follow information on label & instructions regarding installation near combustible materials, insulation, and building materials & in Dry or Wet locations. Do not install in areas exposed to combustible vapors or gases. **This product must be installed by a person familiar with construction and operation of the product and the hazards involved, in accordance with the applicable installation. Be sure to ground product to avoid potential electrical shock or other potential hazard.** Use of accessory equipment not recommended by the manufacturer or installed inconsistent with instructions may cause an unsafe condition. Do not completely or partially block light emerging from product, as this could cause an unsafe condition. Do not allow other items to come into contact with the product, as this may cause an unsafe condition. **WARNING:** This product may contain chemicals known to the State of California to cause cancer, birth defects and/or other reproductive harm. Thoroughly wash your hands after installing, servicing, handling, cleaning, or otherwise touching this product. This device complies with FCC CFR Title 47 Part 15, Class A requirements for EMI/RFI.

WIRE GUARD INSTALLATION

Fig. 1 a



Step 1: Installation of Security Tether

Push steel tie through slot at either end of fixture.

Fig. 1 b






Fig. 2



Step 2: Installation of Diffusor

Install diffusor (if applicable) by wrapping around fixture body leaving both ends of the steel tie exposed.

Fig. 3



Step 3: Add Mounting Clips

Install wire guard mounting clips at each of the four corners.


Fig. 4



Step 4: Tighten Mounting Clips

Snap the mounting clip to the wire guard, then position as shown and tighten thumb screw.

Fig. 5



Step 5: Complete Installation

Complete installation of security tether. Insert tag end into grip and pull to form a loop. Leave enough slack for cleaning and possible service.