

Product Specifications – Dialog® System

1. PART 1 - General

1.1 Overview

- 1.1.1 Provide a complete low voltage lighting control system for the building as shown on the plans and specified herein.
- 1.1.2 Lighting control system shall utilize networking technology connecting relay panels, switches and sensors based upon a 2-wire data line providing both power and data to all field devices. The network shall be free topology; therefore a serial loop is not necessary to achieve maximum network distance. The system shall utilize a web server device complete with a touch screen located in a relay panel so that programming and viewing of status can be accomplished at the panel or by any PC connected to the same LAN or via the internet.
- 1.1.3 All relay panel interiors shall be pre-assembled complete with the necessary relays, transformers and devices. Relay panels that are wall mounted shall have interiors separate from enclosure so as to permit easy mounting, conduit installation and wire pull to enclosures. Enclosures mounted in the ceiling space are not required to have separate interiors.

1.2 Manufacturers

- 1.2.1 All components are to be supplied by same manufacturer. Manufacturer to be a supplier of this type of equipment for over 10 years.
- 1.2.2 Lighting control system shall be the Dialog system manufactured by **Douglas Lighting Controls Inc.**

1.3 Prior Approval Submissions

- 1.3.1 Manufacturers wishing to submit quotations on the lighting control system must pre-qualify. Pre-qualification information must be submitted to the electrical consulting engineer not later than ten (10) working days prior to the final closing of tenders for this project.
- 1.3.2 The manufacturer must be prepared to demonstrate the equipment being proposed before the closing of tender.
- 1.3.3 Submit a one-line diagram of the proposed system configuration for review.

1.4 Instruction Manuals

- 1.4.1 Supply manuals on system components to permit ease of installation, system operation and maintenance including, but not limited to the following:
 - Lighting control system step-by-step operating instructions.
 - Relay panel schedules indicating circuits connected, inputs assigned, area controlled, panel location and panel equipment details.

Universal Douglas

2. PART 2 - Materials

2.1 Relays

- 2.1.1 Lighting control relays shall be mechanically latching and shall come complete with a manual ON/OFF switch. The mechanical switch shall continuously display the true state of the relay's internal contacts.
- 2.1.2 Single pole relays shall be rated and UL/CSA listed for 120VAC, 277VAC and 347VAC lighting loads at 20 amps (30A General Use) and have a general, tungsten, standard and electronic ballast rating. Use **Panasonic** WR-6161K-84.
- 2.1.3 Double pole relays shall be rated and UL listed for 208VAC, 240VAC and 480VAC and CSA for up to 347VAC lighting loads at 20 amps and have a general, tungsten, standard and electronic ballast rating. Use **Panasonic** WR-6172.
- 2.1.4 The relays shall have a label indicating the short circuit fault current rating as per the NEC. The relays shall have passed UL 508 short circuit tests at 18,000 amperes.
- 2.1.5 Each lighting control relay shall be capable of controlling incandescent, fluorescent, electronic ballast and H.I.D. lighting loads and have an inrush capability of 3000 amperes. Relays shall be complete with a 5-year Manufacturer's Limited Warranty.
- 2.1.6 Lighting control relays shall include captive screw terminals for both the line voltage and the low voltage connections. Switching the relay shall be accomplished with ONE signal wire and a common return. The signal wire shall be able to signal ON and OFF and shall carry status current that indicates if the relay is ON or OFF.

2.2 Pre-assembled Relay Panels: PWEx Series

- 2.2.1 Where indicated on the drawings, provide a factory pre-assembled relay panel. The panel's enclosure shall be for surface or flush installation, with a screw-on cover or a hinged door assembly as required.
- 2.2.2 The panel shall consist of a pre-assembled interior insert; UL/CSA approved **Douglas Lighting Controls** CxxM or WxxM series with capacities for 6, 12, 24, 48 or 72 relays as required. Panel enclosure must be UL/CSA Approved.
- 2.2.3 Panel interior shall have the following pre-assembled and pre-wired:
 - Suitable divider separating class 1 and class 2 compartments.
 - Dual-Tap Control transformer, UL/CSA approved for class 2 circuits, Douglas Lighting Controls WR-4075-xxx where xxx = primary voltage.
 - Low voltage relays as required by switched circuits shown on plans or schedules.
 - Control devices as required
- 2.2.4 Relay panels may be CheckLight™ Equipped to support energy measurement and energy management requirements.

Universal Douglas

2.3 Energy Measurement and Energy Monitoring – CheckLight™ by Douglas Lighting Controls

- 2.3.1 The networked lighting control system shall provide energy consumption of the controlled load.
- 2.3.2 The networked lighting control system shall aggregate energy consumption data and present it through a cloud-based Graphical User Interface (GUI).
- 2.3.3 The energy consumption shall present data in time periods of day, week, month, year, as well as offer custom date fields.
- 2.3.4 The energy consumption shall be presentable by zone, multiple-zone, and entire building views.
- 2.3.5 The energy measurement and energy monitoring system shall allow Automated Demand Response (OpenADR) commands to be executed.
- 2.3.6 The energy measurement and energy monitoring system shall allow remote access to the Lighting Control Unit (LCU) for configuration & control of the lighting system.
- 2.3.7 The energy measurement and energy monitoring system shall report system faults by email to a designated person.

2.4 Device Network Controls - Lighting Control Unit: WLC-4150

- 2.4.1 The **Douglas Lighting Controls** Dialog WLC-4150 Lighting Control Unit (LCU) shall be able to operate the local lighting control system on a stand-alone basis. For large installations that require multiple LCUs, all units must be able to operate on a stand-alone basis should they become disconnected from the network.
- 2.4.2 The LCU shall provide the following user interfaces for viewing and editing data:
 - Built-in touch screen with a static IP address field for convenient at panel configuration and providing web accessible configuration.
 - Built-in web server, accessed via TCP/IP connection.
 - LCU shall be accessible via a web browser with no additional software or plug-in required.
- 2.4.3 Each LCU shall provide the following standard lighting control functions:
 - Program and control up to 252 relays and 252 dimmers.
 - Link Outputs to switches and/or sensors to provide ON/OFF, Preset, or Dim Up/Down commands. In addition, functions such as Flick Warn, Time Out, Natural Daylight harvesting, Input and Output Blocks and Quiet Time can be associated with switches, sensors and relays and have these features scheduled by time-of-day or date.
 - Be able to group Outputs and Inputs to facilitate various control schemes.
 - Photo Sensor to provide Dusk-to-Dawn (switching) and/or Natural Daylight (dimming) with multiple set points to different groups.
 - Astronomic Controls for Dusk-to-Dawn applications not requiring Photo Sensor.
 - Provide Log Reports for diagnostic and run-time tracking purposes.

Universal Douglas

Universal Douglas – Canada Office
280-3605 Gilmore Way Burnaby, BC V5G 4X5, Canada
Phone: 877-873-2797

Universal Douglas – United States Office
51 Century Blvd. Ste 230, Nashville, TN 37214
Phone: 615-315-5100

- Time Schedule types include: 7-day weekly scheduling, 365-day date specific, Holiday, and event scheduling.

2.4.4 The system shall have pre-defined logical applications for lighting controls.

- Astronomical Time Clock
- Natural Daylight (CLC) – Open Loop & Close Loop
- Exterior Threshold Photo Control
- Time Out (Unoccupied Mode)
- Quiet Mode
- Permanent Block
- Flick Warn
- Behaviours (Sequencer)
- Triggers

2.4.5 The system must have the ability to operate multiple items and modes with a single action and sequence them with time offsets.

2.4.6 **Behaviors:** The system shall have the ability to program multiple actuations and modes with a single activation. Each item must be able to be programmed with a time offset. When the deactivation occurs a separate and unique list of actuations can be programmed.

2.4.7 **Triggers:** The system shall be able to utilize the status or the one or many relay/group statuses to send an actuation to the system. The statuses must be able to be programmed in an AND or OR logic.

2.4.8 Each LCU shall provide the following system functions:

- Demand response: connection via contact input.
- Accept configuration updates via USB port or Ethernet connection.
- Backup data via Ethernet or USB port
- The device shall be BACnet Native
- Have the capability to connect to CheckLight™ by Douglas Lighting Controls.

2.5 Dialog Room Controller: WRC-4244

2.5.1 Where indicated on the drawings provide a pre-configured, digitally addressable, plenum-rated room controller.

2.5.2 The Dialog Room Controller shall be capable of:

- Autonomously controlling a space.
- Networking to a central Dialog control system.
- Networking to a central BACnet based management system.
- Interconnect multiple WRC-4222/WRC-4244/WUL-4924 in combination up to 12 Relays and Dimmer outputs for stand-alone operation.

2.5.3 The Dialog Room Controller shall consist of:

- A universal voltage type (120VAC/277VAC/347VAC) power supply.
- Four 20A rated relays complete with manual override. Circuit Load rating dependent on usage. One circuit dedicated for 20A receptacle control.
- Four 0-10V control channels, each capable of 100mA current sinking
- A port to connect downstream switches, occupancy sensors and daylight sensors. All downstream

Universal Douglas

devices shall be connected via two #18AWG, non-polarized, non-shielded, non-twisted conductors. See Section 3.4 for wiring specifications.

- A port to connect to an upstream Dialog Lighting Control Unit.
- A port to connect upstream to BACnet IP building management system. The Controller shall communicate using native BACnet command objects appropriate for the application.
- An indicating LED to aid in locating the controller in a darkened ceiling space.
- Circuit testing buttons
- Capable of connecting with WUL-4924
- Dataline Output 24Vac 120mA
- US & Canada Plenum Rated

2.5.4 Relay Ratings

- 20A Suitable for General Purpose Loads @ 120/277/247VAC
- 20A Suitable for Standard Ballasts and Tungsten Loads @ 120/277VAC
- 15A Suitable for Standard Ballasts Only @ 347VAC
- 16A Suitable for Electronic Ballasts @ 120/277VAC
- 0.5HP @120/277VAC

2.5.5 The Dialog Room Controller relays shall be connected such that 120Vac plug load(s) and 277VAC/347VAC lighting loads can be switched by a single Controller with no additional add-ons or remote modules

2.5.6 The Dialog Room Controller shall mount to electrical junction box via threaded ½" chase nipple. No other mounting hardware shall be required.

2.6 Dialog Room Controller: WRC-4222

2.6.1 Where indicated on the drawings provide a pre-configured, digitally addressable, plenum-rated room controller.

2.6.2 The Dialog Room Controller shall be capable of:

- Autonomously controlling a space.
- Networking to a central Dialog control system.
- Networking to a central BACnet based management system.
- Interconnect multiple WRC-4222/WRC-4244/WUL-4924 in combination up to 12 Relays and Dimmer outputs for stand-alone operation.

2.6.3 The Dialog Room Controller shall consist of:

- A universal voltage type (120VAC/277VAC/347VAC) power supply.
- Two 20A rated relays complete with manual override. Circuit Load rating dependent on usage.
- Two 0-10V control channels, each capable of 100mA current sinking
- A port to connect downstream switches, occupancy sensors and daylight sensors. All downstream devices shall be connected via two #18AWG, non-polarized, non-shielded, non-twisted conductors. See Section 3.4 for wiring specifications.
- A port to connect to an upstream Dialog Lighting Control Unit.
- A port to connect upstream to BACnet IP building management system. The Controller shall communicate using native BACnet command objects appropriate for the application.
- An indicating LED to aid in locating the controller in a darkened ceiling space.
- Circuit testing buttons

Universal Douglas

- Capable of connecting with WUL-4924
 - Dataline Output 24Vac 120mA
 - US & Canada Plenum Rated
 - 2.6.4 Relay Ratings
 - 20A Suitable for General Purpose Loads @ 120/277/247VAC
 - 20A Suitable for Standard Ballasts and Tungsten Loads @ 120/277VAC
 - 15A Suitable for Standard Ballasts Only @ 347VAC
 - 16A Suitable for Electronic Ballasts @ 120/277VAC
 - 0.5HP @120/277VAC
 - 2.6.5 The Dialog Room Controller relays shall be connected such that 120Vac plug load(s) and 277VAC/347VAC lighting loads can be switched by a single Controller with no additional add-ons or remote modules
 - 2.6.6 The Dialog Room Controller shall mount to electrical junction box via threaded ½" chase nipple. No other mounting hardware shall be required.
- 2.7 Dialog Room Controller UL924 Relay Expansion Pack: WUL-4924**
- 2.7.1 Where indicated on the drawings provide a 2-relay expansion pack consisting of two independently controllable, 20A relays capable of emergency lighting circuit control.
 - 2.7.2 Expansion pack relays shall force EM lights on when the Dialog Room Controller loses power.
 - 2.7.3 The expansion pack shall connect to the Dialog Room Controller. No wires or tools shall be required to add an expansion pack to a Dialog Room Controller. The Dialog Room Controller will include a means for remote mounting if required.
 - 2.7.4 Circuit testing buttons
 - 2.7.5 The device must be UL-924 certified
 - 2.7.6 Capable of connecting directly to WRC-4244 & WRC-4222
- 2.8 Relay controls installed in relay panels - Relay Drivers: WRD-3408z**
- 2.8.1 The low voltage relays shall be connected to the Dialog system by a Douglas Lighting Controls WRD-3408z relay driver unit. Each WRD-3408z relay driver has 8 outputs and shall provide enough relay driver units so that each relay in the system is connected to an output.
 - 2.8.2 Relay drivers shall be able to control relays ON and OFF, determine relay status, provide feedback as to whether a relay is connected and be addressable within the Dialog network.
- 2.9 Dimming Ballast Control - Ballast Drivers: WDB-3314**
- 2.9.1 The Dialog system shall be able to control industry standard 0-10VDC dimming ballasts or 0-10VDC LED drivers by using the **Douglas Lighting Controls WDB-3314 Dimming Ballast Module**. Each WDB-3314 shall have 4 dimming address

Universal Douglas

Universal Douglas – Canada Office
280-3605 Gilmore Way Burnaby, BC V5G 4X5, Canada
Phone: 877-873-2797

Universal Douglas – United States Office
51 Century Blvd. Ste 230, Nashville, TN 37214
Phone: 615-315-5100

www.universaldouglas.com | www.unvlt.com | www.douglaslightingcontrols.com

outputs, be able to support 35 ballasts per output and support sink current of 100mA per output.

2.10 Contact Input: WCI-3928

2.10.1 Use a **Douglas Lighting Controls** WCI-3928 when inputs from other devices (including other manufacturers) are required. Each unit shall provide DC power for each sensor and will accept a momentary or maintained contact signal from each sensor that can be assigned to any relay or group. Check with factory to ensure compatibility.

2.10.2 Devices connected to WCI-3928 input unit shall include the following features:

- Function selection: ON only, OFF only, toggle (ON/OFF)
- Multiple sensors may work together using either direct connection to sensors or via multi-sensor function built into WCI-3928 units.

2.11 BACnet

2.11.1 The LCU shall be BACnet native and have the ability to communicate to a system integrator or other software specialist. It shall be possible to view/control the system via the BACnet integration software through TCP/IP connection. The system shall provide the following features:

- Program and control up to 252 relays and dimming points.
- Control and receive status for Groups
- Control and receive status for Presets
- Receive status from Occupancy Sensors

2.11.2 Alternatively, a WNG-3131 Dialog BACnet IP gateway can be provided if IT system isolation is required.

2.12 Global Web Server: GWS-xxxx

2.12.1 The **Douglas Lighting Controls** GWS-xxxx shall be able to operate the entire lighting control system from a single interface.

2.12.2 The GWS shall provide the built-in web server interfaces for viewing and editing data, accessed via TCP/IP connection and connect to a PC/laptop using IE9 or above.

2.12.3 The GWS will provide access to up to 25 LCUs and shall provide the following standard lighting control functions within **each** LCU:

- Program and control up to 252 relays and 252 dimmers.
- Link Outputs to switches and/or sensors to provide ON/OFF, Preset, or Dim Up/Down commands. In addition, functions such as Flick Warn, Time Out, Natural Daylight, Enable/Disable and Quiet Time can be associated with switches, sensors and relays and have these features scheduled by time-of-day or date.
- Be able to group Outputs and Inputs to facilitate various control schemes.
- Photo Sensor to provide Dusk-to-Dawn (switching) and/or Natural Daylight (dimming) with multiple set points to different groups.
- Astronomic Controls for Dusk-to-Dawn applications not requiring Photo Sensor.
- Provide log reports for diagnostic and run-time tracking purposes.
- Time schedule types include: 7-day weekly scheduling, 365-day date specific and event scheduling.

Universal Douglas

Universal Douglas – Canada Office
280-3605 Gilmore Way Burnaby, BC V5G 4X5, Canada
Phone: 877-873-2797

Universal Douglas – United States Office
51 Century Blvd. Ste 230, Nashville, TN 37214
Phone: 615-315-5100

- 2.12.4 The **GWS-xxxx** shall provide the additional following system functions:
- Centralized Programming
 - Synchronization of time clocks
 - Download and upload of all system files
 - OPC Server Deployment
 - The ability to host the Graphics Package to operate with an GUI interactive floor plan

2.13 Graphics Package

- 2.13.1 In normal operation / manual command mode, the computer shall enable the viewing of one or more graphic drawings of the controlled building along with the status of each of the controlled sectors. Using the mouse or optional Touch Screen, the operator can view into various portions of the building and switch relays, groups, presets, and active modes. No special control code memorization shall be necessary.
- 2.13.2 The owner shall provide direction on colors and logos
- 2.13.3 The lighting symbols shall be established by the user through the graphic editor and shall change color in order to display the real time status of that particular relay or zone.
- 2.13.4 The Graphics shall be deployed on the **Douglas Lighting Controls** GWS Global Web Server (GWS) and served up via a mobile or desktop browser.

2.14 Wall Switch – WSW-45xx series Data Line Switches

- 2.14.1 Switches shall be **Douglas Lighting Controls** WSW-45xx and connect to the lighting control network via a common 2-wire, non-polarized data line. Switches shall be configured and programmed to control one or more outputs in the lighting control system.
- 2.14.2 Switches shall have the capability to be configured by a **Dialog 4000 Series Programmer App** for Apple iOS or Android that accesses programming fields of the switch without removing the switch from the wall box.
- 2.14.3 Switches shall have a companion app to allow for touchless control of the switch station via the **Dialog Tap-to-Control App** for Apple iOS or Android.
- 2.14.4 Switches are linked to a single output or a group of outputs.
- 2.14.5 Switches, Occupancy Sensors and Photo Sensors can be set to a common output address to permit multiple points of control for a single relay or dimming output.
- 2.14.6 Switches, Occupancy Sensors and Photo Sensors can be set to a common group address to permit multiple points of control for a group of outputs.
- 2.14.7 Each switch can be programmed for ON/OFF control of outputs, UP/DOWN control of 0-10VDC dimming ballasts, 0-10VDC LED drivers and/or preset control to set a specific lighting scene.
- 2.14.8 Each switch shall allow button configurations for a timer function.
- 2.14.9 Switches, with LED indicators to indicate both ON and OFF output/group status, shall be available with 1, 2, 4, 6, or 8 single button switches per gang.

Universal Douglas

- 2.14.10 Switches and switch hardware shall mount to standard wall boxes and fit standard Decora opening.
- 2.14.11 Default labeling provided for a simple usage and esthetics, each switch shall allow custom laser-etching, if required.
- 2.14.12 Adhere to the factory recommended wiring practices so that physical removal of any single switch shall still permit communication between relay panels in the rest of the Dialog lighting control network.

2.15 Dimmer Switch: WSD-450x series

- 2.15.1 Dimmer switches shall be **Douglas Lighting Controls WSW-45xx** and connect to the lighting control network via a common 2-wire, non-polarized data line. Switches shall be configured and programmed to control one or more outputs in the lighting control system.
- 2.15.2 Dimmer switches shall have the capability to be configured by a **Douglas Lighting Controls 4000 Series Programmer App** for Apple iOS or Android App that accesses programming fields of the switch without removing the switch from the wall box.
- 2.15.3 Dimmer switches shall have a companion app to allow for touchless control of the switch station via the **Dialog Tap-to-Control App** for Apple iOS or Android.
- 2.15.4 Dimmer switches, with LED indicators to indicate both ON and OFF output/group status, shall be available with 1, 2, or 4 zones of ON/OFF and Dimming per gang.
- 2.15.5 Switches and switch hardware shall mount to standard wall boxes and fit standard Decora opening.
- 2.15.6 Default labeling provided for a simple usage and esthetics, each switch shall allow custom laser-etching, if required.
- 2.15.7 Adhere to the factory recommended wiring practices so that physical removal of any single switch shall still permit communication between relay panels in the rest of the Dialog lighting control network.

2.16 Keyed Switch: WSK-3502 series

- 2.16.1 Keyed switches shall be **Douglas Lighting Controls WSK-3502** and connected to the lighting control network via a 2-wire, non-polarized data line.
- 2.16.2 Keyed ON/OFF switches shall include LED indicators for ON and OFF status.
- 2.16.3 Keyed switches can be programmed to control individual outputs or groups of output and can also be programmed to enable/disable peripheral devices such as switches or sensors.
- 2.16.4 Each keyed action, clockwise and counter-clockwise, shall allow for independently programmed functions.
- 2.16.5 Keyed switches can be programmed with a **Douglas Lighting Controls WIR-3110** infrared setting unit.

Universal Douglas

- 2.17 LCD Switch: WSW-LCD**
- 2.17.1 A wall station switch with an LCD graphical user interface shall be **Douglas Lighting Controls WSW-LCD** and connect to the lighting control network via a 2-wire, non-polarized data line and require a 24VAC power supply.
 - 2.17.2 The LCD wall station switch shall have a touch screen interface.
 - 2.17.3 The LCD wall station switch shall be installed into a two-gang wall station box.
- 2.18 Ceiling Occupancy/Vacancy Sensor: Low Voltage WORxDG1-BPR-N Series**
- 2.18.1 Sensors shall be **Dialog WORxDG1-BPR-N** series, Dual Technology with Passive Infrared (PIR) and ADI-Voice detection.
 - 2.18.2 Sensors shall be network connected using #18AWG two wire providing power and data bus.
 - 2.18.3 Ceiling sensors shall mount recessed in to the ceiling space.
 - 2.18.4 Sensors shall have a 360 degree coverage pattern with an adjustable tilt head to maximize coverage, focus on particular areas, or provide adjustment when mounted on sloped ceilings.
 - 2.18.5 Lenses shall be available in Standard, Extended, Highbay, and Aisleway.
 - 2.18.6 Sensors shall provide an adjustable time out period of 12 seconds to 60 minutes.
 - 2.18.7 Sensors shall include a prolong feature allowing for a delay period before unoccupied state occurs. When enabled, the lights can be in an additional lighting state before shutting off.
 - 2.18.8 If a Photo Sensor is required, it shall be incorporated into the Occupancy Sensor device and shall be used for Daylight Harvesting functions.
 - 2.18.9 A Form-C relay shall be provided to allow for signaling to other systems, such as an AHU.
 - 2.18.10 A Manual Override Switch is to be provided on the sensor to allow the load to be manually switched ON and OFF for the purpose of testing during installation.
- 2.19 Wall Station Occupancy/Vacancy Sensor and Switch: Low Voltage WOSSDG1-BP-VW**
- 2.19.1 Sensors shall be **Dialog WOSSDG1-BP-VW** Dual Technology sensor with Passive Infrared (PIR) and ADI-Voice detection.
 - 2.19.2 Sensors shall be network connected using #18AWG two wire providing power and data bus.
 - 2.19.3 Sensors shall provide an adjustable time out period of 12 seconds to 60 minutes.
 - 2.19.4 Sensors shall include a prolong feature allowing for a delay period before unoccupied state occurs. When enabled, the lights can be in an additional lighting state before shutting off.
 - 2.19.5 If a Photo Sensor is required, it shall be incorporated into the Occupancy Sensor device and shall be used for Daylight Harvesting functions.
 - 2.19.6 Switches and switch hardware shall mount to standard wall boxes and fit standard Decora opening.

- 2.19.7 A Manual Override Switch is to be provided on the sensor to allow the load to be manually switched ON and OFF for the purpose of testing during installation and for MANUAL ON/AUTO OFF (vacancy) applications.

**2.20 Wall Station Occupancy/Vacancy Sensor and Dimmer:
Low Voltage WOSSDG1-BDP-VW**

- 2.20.1 Sensors shall be **Dialog WOSSDG1-BDP-VW** Dual Technology sensor with Passive Infrared (PIR) and ADI-Voice detection.
- 2.20.2 Sensors shall be network connected using #18AWG two wire providing power and data bus.
- 2.20.3 Sensors shall provide an adjustable time out period of 12 seconds to 60 minutes.
- 2.20.4 Sensors shall include a prolong feature allowing for a delay period before unoccupied state occurs. When enabled, the lights can be in an additional lighting state before shutting off.
- 2.20.5 If a Photo Sensor is required, it shall be incorporated into the Occupancy Sensor device and shall be used for Daylight Harvesting functions.
- 2.20.6 Switches and switch hardware shall mount to standard wall boxes and fit standard Decora opening.
- 2.20.7 A Manual Override Switch is to be provided on the sensor to allow the load to be manually switched ON and OFF for the purpose of testing during installation and for MANUAL ON/AUTO OFF (vacancy) applications.
- 2.20.8 The Dimmer version (-BDP) has a raise and lower button for dimming targets on the Dialog bus.

2.21 Wall Sensor: Low Voltage WOW Series

- 2.21.1 Sensors shall be **Dialog WOW** series Dual Technology with Passive Infrared (PIR) and ADI-Voice detection.
- 2.21.2 Sensors shall be network connected using #18AWG two wire providing power and data bus
- 2.21.3 Sensors shall have a pivoting head to maximize coverage, focus on particular areas, or provide adjustment when mounted on sloped ceilings.
- 2.21.4 Sensors shall provide an adjustable time out period of 30 seconds to 30 minutes.
- 2.21.5 If a Photo Sensor is required, it shall be incorporated into the Occupancy Sensor device and operate so that when occupancy is detected, the sensor will only allow the load to be switched ON if the light level is below the daylight level set by the user.

2.22 Photo Sensor & Daylight Controls: WPS-3741B Exterior Daylight Sensor

- 2.22.1 Provide where required a **Douglas Lighting Controls WPS-3714B** Exterior Daylight Sensor capable of sensing from 0 to 65,000 lux (0 to 6500 fc) of direct

Universal Douglas

light. The sensor shall derive both its power and data information from the **Dialog** data line.

- 2.22.2 The ambient light level shall be continuously monitored in lux by the sensor. The sensor shall broadcast to the network the existing light level when requested or when there is a change in detected light level.
- 2.22.3 Set point adjustments can be made via a touch screen or web server interface to the **Douglas Lighting Controls WLC-4150 LCU** or on the WLC-4150.
- 2.22.4 Each sensor can be programmed to provide ON/OFF control of relays, raise/lower of 0-10vdc ballasts and LED drivers via a touch screen or web server interface to the **Douglas Lighting Controls WLC-4150 LCU** or on the WLC-4150.
- 2.22.5 One sensor shall permit different outputs to switch and/or control light levels as ambient light changes. Light levels shall be controlled by 'sensor only' or in combination with a time schedule or with a dimming switch.
- 2.22.6 It shall be possible to set a maximum light level which cannot be exceeded during Natural Daylight operations or for non-daylight controlled areas, a permanent or "tuned" light level to maximize energy savings.

2.23 Photo Sensor & Daylight Controls: WPS-4741 Interior Daylight Sensor

- 2.23.1 Provide where required a **Douglas Lighting Controls WPS-4741 Interior Daylight Sensor** capable of sensing from 0 to 65,000 lux (0 to 6500 fc) of direct light. The sensor shall derive both its power and data information from the **Dialog** data line.
- 2.23.2 The ambient light level shall be continuously monitored in lux by the sensor. The sensor shall broadcast to the network the existing light level when requested or when there is a change in detected light level.
- 2.23.3 Set point adjustments can be made via a touch screen or web server interface to the **Douglas Lighting Controls WLC-4150 LCU** or on the WLC-4150.
- 2.23.4 Each sensor can be programmed to provide ON/OFF control of relays, raise/lower of 0-10vdc type or ballasts and LED drivers via a touch screen or web server interface to the **Douglas Lighting Controls WLC-4150 LCU** or on the WLC-4150.
- 2.23.5 One sensor shall permit different outputs to switch and/or control light levels as ambient light changes. Light levels shall be controlled by 'sensor only' or in combination with a time schedule or with a dimming switch.
- 2.23.6 It shall be possible to set a maximum light level which cannot be exceeded during Natural Daylight operations or for non-daylight controlled areas, a permanent or "tuned" light level to maximize energy savings.

2.24 Infrared Setting Unit: WIR-3110

- 2.24.1 Provide a **Douglas Lighting Controls WIR-3110 Infrared Setting Unit** to facilitate the following functions:

- Set input device and address
- Configure input device presets, group, and individual control
- Set local or global functionality

Universal Douglas

2.25 Wireless Devices: Bluetooth® Dimmer Switch

- 2.25.1 Dimmer switches shall be **Douglas Lighting Controls BT-DMSW-***
- 2.25.2 Wireless dimmer switches shall communicate with Douglas Lighting Controls wireless devices via Douglas Lighting Controls' wireless Bluetooth® mesh.
- 2.25.3 Each wireless dimmer switch shall be capable of raising or lowering light levels of individual or groups of lighting fixtures.
- 2.25.4 Wireless dimmer switches shall include integrated LED indicators for light levels as well as an ON/OFF switch.
- 2.25.5 Wireless dimmer switches shall be configurable with a Douglas Lighting Controls' smartphone Bluetooth App – **BT-APP**.

2.26 Wireless Devices: Bluetooth 4 & 8 Button Switches

- 2.26.1 Wireless Switches shall be **Douglas Lighting Controls BT-4BTSW-*** and **BT-8BTSW-*** switches.
- 2.26.2 Wireless switches shall communicate with Douglas Lighting Controls wireless devices via Douglas Lighting Controls' wireless Bluetooth mesh.
- 2.26.3 Wireless switches shall be configured and programmed to control one or more outputs in the lighting control system.
- 2.26.4 Wireless Switches shall be programmed with a Douglas Lighting Controls' smartphone Bluetooth App – **BT-APP**.
- 2.26.5 Each wireless switch can be programmed for ON/OFF control of outputs, UP/DOWN control of 0-10VDC dimming ballasts, 0-10VDC LED drivers and/or preset control to set a specific lighting scene.
- 2.26.6 Wireless Switches, with LED indicators to indicate both ON and OFF output/group status, shall be available with 4 or 8 single button switches per gang.
- 2.26.7 Wireless Switches to fit standard Decora opening.
- 2.26.8 Wireless Switches and switch hardware shall mount to standard wall boxes.
- 2.26.9 Each wireless switch shall provide a location for a label to identify function. The label shall be under a clear plastic cover and shall be field replaceable should the operation of the switch change. Permanently etched switches are not acceptable.

2.27 Wireless Devices: Bluetooth Sensor

- 2.27.1 Wireless Occupancy and Daylight Sensors shall be Douglas Lighting Controls Dual Technology **BT-WOR-*** ceiling mounted sensors.
- 2.27.2 Wireless switches shall communicate with Douglas Lighting Controls wireless devices via Douglas Lighting Controls' wireless Bluetooth mesh.
- 2.27.3 Wireless ceiling sensors shall have an integrated ceiling tile cutting tool for mounting the sensor without tools.
- 2.27.4 Wireless ceiling sensors shall have a friction mount surface to eliminate a mounting bracket or screws to hold the sensor in place.

Universal Douglas

- 2.27.5 Wireless Sensors shall have a 13/16" lens that provides a 360 degree coverage pattern to maximize coverage.
- 2.27.6 Wireless Sensors shall provide an adjustable time-out period of 30 seconds to 30 minutes.
- 2.27.7 Wireless Sensors shall have power provided from a 12VDC source.
- 2.27.8 The ambient light level shall be continuously monitored in lux by the wireless sensor.
- 2.27.9 The wireless sensor shall broadcast to the Douglas Lighting Controls wireless network the existing light level when requested or when there is a change in detected light level.
- 2.27.10 Set point adjustments can be made via Smartphone App from **Douglas Lighting Controls** BT-APP.
- 2.27.11 Each wireless sensor shall have the ability to send wireless Bluetooth messages to a Douglas Lighting Controls **BT-PP20-*** wireless Bluetooth controller to provide ON/OFF control of relays; raise/lower 0-10VDC ballasts and LED drivers; and operate a close loop controlled daylight harvesting system.
- 2.27.12 It shall be possible to set a maximum light level which cannot be exceeded during Natural Daylight operations or for non-daylight controlled areas, a permanent or "tuned" light level to maximize energy savings.

2.28 Wireless Devices: Bluetooth Load Controller

- 2.28.1 A wireless load controller from Douglas Lighting Controls BT-PP20-B shall be used for providing wireless Bluetooth mesh network control to one or multiple fixtures.
- 2.28.2 Wireless load controller shall communicate with Douglas Lighting Controls wireless devices via a Bluetooth mesh network
- 2.28.3 Wireless load controllers shall be powered by 120VAC, 277VAC or 347VAC line voltages.
- 2.28.4 Wireless load controllers shall provide 0-10V dimming control
- 2.28.5 Wireless load controllers shall provide a 12VDC output for powering a Douglas Lighting Controls occupancy and daylight sensor – **BT-WOR-***
- 2.28.6 Wireless load controllers shall have a threaded chase nipple for installation into a standard ½" knockout and have flying leads for connecting to line voltage and to the fixture's 0-10V dimming
- 2.28.7 Wireless load controller shall support plug load control applications
- 2.28.8 Wireless load controller shall be CheckLight Equipped to support energy measurement and energy management requirements

2.29 Wireless Controller and Sensor for Luminaire Level Lighting Controls: BT-IFS

- 2.29.1 Provide a wireless controller and occupancy sensor from Douglas Lighting Controls (BT-IFS) for providing wireless Bluetooth network control to a fixture
- 2.29.2 Include two 0-10v dimming channels
- 2.29.3 Support power input from either 12VAC or 24VAC

Universal Douglas

- 2.29.4 Support Tunable White luminaires with a 12VAC or 24VAC auxiliary output and two 0-10V dimming channels
- 2.29.5 Provide a PIR Occupancy sensor with a maximum lens range of 5m (16.4 feet)
- 2.29.6 Provide a Secondary sensing technology using Bluetooth beacon
- 2.29.7 Use a Bluetooth wireless technology to communicate with other Douglas Lighting Controls Bluetooth enabled devices
- 2.29.8 Use a Bluetooth wireless technology for device and network configuration
- 2.29.9 Provide an Apple® iOS App available for free on the Apple App Store for device and network configuration
- 2.29.10 Provide an Apple iOS App available for free on the Apple App Store for end-user room control
- 2.29.11 Be installed into an industry standard ½” electrical knockout using a tool-less friction fit with a silicon retention ring
- 2.29.12 Provide a 4-terminal push in connector
- 2.29.13 Sink up to 25mA per 0-10V dimming channel
- 2.29.14 Provide a Bluetooth beacon for Location Service projects

2.30 Wireless Controller for Luminaire Level Lighting Controls: BT-IFC

- 2.30.1 Provide a wireless controller from Douglas Lighting Controls (BT-IFC) to be used for providing wireless Bluetooth network control to a fixture
- 2.30.2 Support power input from either 12VAC or 24VAC
- 2.30.3 Support Tunable White luminaires with a 12VAC or 24VAC auxiliary output and two 0-10V dimming channels
- 2.30.4 Provide a PIR Occupancy sensor with a maximum lens range of 5m (16.4 feet)
- 2.30.5 Use a Bluetooth wireless technology to communicate with other Douglas Lighting Controls Bluetooth enabled devices
- 2.30.6 Use a Bluetooth wireless technology for device and network configuration
- 2.30.7 Provide an Apple iOS App available for free on the Apple App Store for device and network configuration and user room control
- 2.30.8 Be installed into an industry standard ½” electrical knockout using a tool-less friction fit with a silicon retention ring
- 2.30.9 Provide a 4-terminal push in connector
- 2.30.10 Sink up to 25mA per 0-10V dimming channel
- 2.30.11 Provide a Bluetooth beacon for Location Service projects

2.31 Wireless Devices: Bluetooth Configuration App

- 2.31.1 A dedicated iOS device shall be provided for the ownership for security and backup purposes.
- 2.31.2 For additional security, a unique iCloud account shall be provided to the ownership that is to be used for commissioning and programming the system.
- 2.31.3 A wireless Bluetooth Smartphone App shall be used for field commissioning of Douglas Lighting Controls Wireless Bluetooth devices.
- 2.31.4 A wireless Bluetooth smartphone app for commissioning shall be available to download at no charge.

2.32 Wireless Devices: Bluetooth Control App

- 2.32.1 A wireless Bluetooth Smartphone App shall be used by the end-user for controlling the wireless Bluetooth mesh network.
- 2.32.2 A wireless Bluetooth app for end-user control shall be available for download.
- 2.32.3 This app shall be available on Apple iOS and Android.

Universal Douglas

Universal Douglas – Canada Office
280-3605 Gilmore Way Burnaby, BC V5G 4X5, Canada
Phone: 877-873-2797

Universal Douglas – United States Office
51 Century Blvd. Ste 230, Nashville, TN 37214
Phone: 615-315-5100

3. PART 3 - Installation

3.1 Relay panels and conduit.

- 3.1.1 Ensure that conduit for line voltage wires enters panel in line voltage areas and conduit for low voltage control wires enters panel on low voltage areas. Check manufacturer's drawings for location of line and low voltage areas.

3.2 Daylight Sensors

- 3.2.1 Install **Douglas Lighting Controls** WPS-4741 or WPS-3741B daylight sensors as per manufacturer's recommendations for closed loop and open loop applications. Ensure there is no artificial light shining directly into the sensor head.
- 3.2.2 Adhere to manufacturer's recommendations for wiring and programming.

3.3 Occupancy Sensors

- 3.3.1 Install **Douglas Lighting Controls** Dialog WxRxDG1-BPP-N as per manufacturer's recommendations. Occupancy Sensors so objects do not block the coverage area. Keep away from HVAC vents and light directly from light fixtures.
- 3.3.2 Adhere to manufacturer's recommendations for location, wiring and programming.

3.4 Wiring

- 3.4.1 For low voltage wiring, provide wire type as recommended by the manufacturer.
- 3.4.2 Adhere to manufacturer's recommendations as to maximum wire length and maximum quantity of relays per switch.
- 3.4.3 Dialog Data line shall be single pair #18AWG LVT wire type or equivalent.

3.5 Line Voltage Wiring

- 3.5.1 Use wire gauges from #12AWG to #14AWG as appropriately sized for the branch circuit.

- ### -

7.08.22

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth® SIG, Inc. and any use of such marks by Panasonic is under license. Other trademarks and trade names are those of their respective owners.

Universal Douglas

Universal Douglas – Canada Office
280-3605 Gilmore Way Burnaby, BC V5G 4X5, Canada
Phone: 877-873-2797

Universal Douglas – United States Office
51 Century Blvd. Ste 230, Nashville, TN 37214
Phone: 615-315-5100

www.universaldouglas.com | www.unvlt.com | www.douglaslightingcontrols.com